T U M

I N S T I T U T F Ü R I N F O R M A T I K

A Compositional Partial Order Semantics for Petri Net Components

Ekkart Kindler

TUM-I9613
SFB-Bereich: 342
März 96

T E C H N I S C H E U N I V E R S I T Ä T M Ü N C H E N

TUM-INFO-03-96-I9613-200/1.-FI
Alle Rechte vorbehalten
Nachdruck auch auszugsweise verboten

©96 FAKULTÄT FÜR MATHEMATIK UND
INSTITUT FÜR INFORMATIK
TECHNISCHE UNIVERSITÄT MÜNCHEN

Druck: Fakultät für Mathematik und
Institut für Informatik der
Technischen Universität München

A Compositional Partial Order Semantics for Petri Net Components

Ekkart Kindler*
Humboldt-Universität zu Berlin, Institut für Informatik, D-10099 Berlin, Germany

Abstract

In this paper we introduce the concept of a Petri net component and show how systems can be composed from components. A component communicates with its environment via distinguished input and output places, which formalizes communication by message passing.

Then, we present a compositional semantics for components. The semantics is an extension of processes for place/transition systems (partial order semantics). We show that the semantics is fully abstract with respect to the behaviour of closed components (essentially, processes of place/transition systems). A main feature of the compositional semantics is that composition of components corresponds to conjunction.

The semantics can be easily combined with a temporal logic interpreted on processes of a place/transition system. We introduce such a logic and show how it can be combined with the semantics to achieve a rely-guarantee concept.

Keywords: Petri net component, compositional semantics, rely-guarantee specification, partial order semantics, fully abstract.

Introduction

For a modular design of distributed systems a system must be built from components. Furthermore, it must be easy to derive the behaviour of a composed system from the behaviour of its components. For that reason *compositional semantics* are essential. A compositional semantics, however, is not of great use if it cannot be dealt with in an easy way. To this end, the *rely-guarantee-style* for specifying a component has been propagated [Jon83]: the behaviour of a component is specified in dependency of the behaviour of its environment.

In this paper, we introduce the concept of *Petri net components* — a Petri net equipped with *input* and *output* places. Components can be composed at these input and output places. We present a compositional semantics for components and show how components

*Correspond to: `kindler@informatik.hu-berlin.de`

can be specified in a rely-guarantee-style by help of a temporal logic.

The key idea of the compositional semantics is known from other formalisms [BKP84, Pnu85, AL90, Pan90]: The semantics is a set of runs; in a run of a component we represent transitions of the component as well as possible transitions of its environment. Since we use *partial order semantics* (processes of place/transition nets [GR83]), we can avoid some technical problems occurring in interleaving semantics [AL90]. Therefore, this semantics is particularly appealing — from a theoretical as well as from an application point of view. Though Petri nets are often reputed to be not compositional, there already exists a compositional partial order semantics (and some more compositional interleaving semantics), which was introduced by Mazurkiewicz [Maz88]. Mazurkiewicz' semantics is based on fusion of transitions, which corresponds to synchronous communication (like in CCS). In contrast, we combine components at input and output places, which corresponds to asynchronous communication via message passing.

For the specification of components we introduce a temporal logic, which is interpreted on runs. It is similar to the Petri net logics introduced in [Rei92, GK+93, KW95, Rei95]; but we allow runs which are not 1-safe, too.

1 Introductory example

First, we present a simple example of a Petri net *component*. This example will help to understand the notion of a component and the *composition* of components. Moreover, we motivate the particular choice of our semantics by help of this example.



Figure 1: A channel

Figure 1 shows a Petri net surrounded by a box. Some places are arranged at the border of the surrounding box and are marked by an arrowhead. These places represent the *interface* of the component to its environment. An arrowhead pointing into the box indicates an *input place* of the component on which the environment may put some tokens; the environment may not remove a token from an input place. An arrowhead in the opposite direction indicates an *output place* of the component; the environment is allowed to remove a token from an output place, but may not put a token on it. The component itself may remove tokens from input places and put tokens to output places, but not vice versa. The component of Fig. 1 models a simple bidirectional *channel* between two sites, which we call A and B.

Figure 2 models the behaviour of the two sites A and B. Site A models a producer and

Figure 2: A producer- and a consumer-component

site B models a consumer.

Now, we can *compose* these three components at the corresponding interface places (places with the same name). The composition is shown in Fig 3. In the composition the



Figure 3: Composition of the above components

combined interface places become *internal places*, which are initially unmarked. When two components are composed it may happen, that an interface place of one component has no corresponding interface place in the other component; then, this place will be an interface place in the combined system. In our example, however, there are no interface places in the composed system any more; therefore, we call it a *closed component*. Since the interface places are supposed to model communication by message passing, we do only combine input places of one component with output places of the other (and vice versa). Moreover, an internal place of one component is not allowed to occur in the other component. When two components are not composable for this reason, they must be renamed before.

Hitherto, we have presented the syntactical aspects of components and their composition. The main aspect of this paper, however, is semantics: we want to formalize the behaviour (*semantics*) of a component in such a way, that the behaviour of a composed system can be derived from the behaviour of its components (without knowing the components themselves). Such a semantics is called *compositional* with respect to the composition of components.

The presentation of the compositional semantics needs some prerequisites, which will be given in the subsequent sections. In this informal example we will only motivate the main idea of this semantics: it is necessary to represent some behaviour of the environment of a component in the semantics of a component in order to make it compositional. To see this, we consider the component shown in Fig. 4, which has the same interface as the component *channel* from Fig. 1. When we consider the channel and the *empty* component in isolation



Figure 4: Empty component

(i.e. the environment doesn't put tokens to the input places), they both have the same behaviour: both components do absolutely nothing. Obviously, both components should show different behaviour, when composed with the producer and consumer component. So, if we want to derive the behaviour of a composed system only from the behaviour of its components, it is necessary that the channel and the empty component have different behaviour. Therefore, the semantics of a component *must* consider some aspects of the behaviour of the environment.

In our approach we will adopt a very extreme position, where the semantics of a component explicitly represents the possible behaviour of its environment (cf. [BKP84, Pnu85, AL90]). Though, this approach seems to be naive at first glance, we will show that it is adequate from three different points of view:

Logical: Composition of two components corresponds to conjunction. This has very nice impacts on modular design methods [AL90, AL93] based on this semantics.

Semantical: Our semantics is *fully abstract* with respect to the composition operation and a *reference semantics* for closed components to be defined. Essentially, the reference semantics is the set of processes of a place/transition system [GR83] equipped with the *progress assumption* [Rei87, KW95, Rei95].

Practical: The semantics can be used to design systems in a modular way in combination with a temporal logic interpreted on processes of place/transition systems. In particular, we can specify components in a rely-guarantee-style.

2 Basic definitions

Now, we present the basic notions known from Petri net theory. We use place/transition systems (without capacities and arc-inscriptions) and their processes [GR83] as basic formalism. For simplicity, we consider only *T-restricted*[1] nets of *finite synchronization* [BF88]. Readers familiar with these concepts can quickly skim through this section.
We start with the definition of nets, markings and system nets.

Definition 1 (Net, marking, system net)

A triple $N = (P, T; F)$ is a *net*, if P and T are two disjoint sets and $F \subseteq (P \times T) \cup (T \times P)$.

A *marking* M of net N is a mapping $M : P \rightarrow \mathbb{N}$ such that $\sum_{p \in P} M(p) \in \mathbb{N}$.

A *system net* $\Sigma = (N, M)$ is a net N equipped with a marking M of N. The marking M is called the *initial marking* of Σ.

As usual, elements of P, T, and F are called *places*, *transitions* and *arcs* of the net, and are represented as circles, squares and arrows, respectively. A place or a transition of a net N is called *element* of N.

Definition 2 (Pre- and postset, minimal and maximal elements)

Let $N = (P, T; F)$ be a net and $x \in P \cup T$ be an element of N. The *preset* ${}^\bullet x$ and *postset* $x^\bullet$ of x are defined as ${}^\bullet x \mathrel{\hat{=}} \{y \in P \cup T \mid (y, x) \in F\}$ and $x^\bullet \mathrel{\hat{=}} \{y \in P \cup T \mid (x, y) \in F\}$. For a set of transitions $U \subseteq T$ we define ${}^\bullet U = \bigcup_{t \in U} {}^\bullet t$ and $U^\bullet = \bigcup_{t \in U} t^\bullet$.

The *minimal* and *maximal* elements of N are defined by ${}^\circ N \mathrel{\hat{=}} \{x \in P \cup T \mid {}^\bullet x = \emptyset\}$ and $N^\circ \mathrel{\hat{=}} \{x \in P \cup T \mid x^\bullet = \emptyset\}$, respectively.

A net N is *T-restricted*, if ${}^\circ N \cup N^\circ \subseteq P$. A net N is of *finite synchronization*, if for each transition $t \in T$ the preset and postset is finite.

For simplicity, we adopt the following restrictions:

Convention 1

We consider only nets $N = (P, T; F)$ which are T-restricted and of finite synchronization.

We fix a set S for the rest of this paper and consider only system nets $\Sigma = (N, M)$ with place set $P \subseteq S$ and $T \cap S = \emptyset$.

For a smooth presentation of processes of a system net, we introduce some notations for multisets.

[1] I.e. each transition of the net has a nonempty pre- and postset.

Definition 3 (Multiset notations)

A *multiset over* S is a mapping $M : S \to \mathbb{N}$. For $s \in S$ we write $M[s]$ instead of $M(s)$ to indicate that M is a multiset. We define the relation $\leq$ on multisets pointwise: $M \leq M'$, iff (if and only if) for each $s \in S$ holds $M[s] \leq M'[s]$. Moreover, we define the multiset $M + M'$ pointwise by $(M + M')[s] = M[s] + M'[s]$ for each $s \in S$. A multiset M is *finite*, if $\sum_{s \in S} M[s] \in \mathbb{N}$.

Since we assume $P \subseteq S$ for each net with places P, a marking M of a net can be considered as a multiset over S (with $M[s] = 0$ for $s \notin P$). Vice versa each finite multiset M over S with $M[s] = 0$ for $s \notin P$ can be considered as a marking of a net with places P.

Moreover, for a net $N = (P, T; F)$ and a transition $t \in T$ the preset ${}^\bullet t$ and postset $t^\bullet$ can be considered as multisets. To avoid confusion, we introduce new symbols to denote these multisets: ${}^-t : S \to \mathbb{N}$ and $t^+ : S \to \mathbb{N}$ with

$$ {}^-t[s] = \begin{cases} 1 & s \in {}^\bullet t \\ 0 & s \notin {}^\bullet t \end{cases} \qquad t^+[s] = \begin{cases} 1 & s \in t^\bullet \\ 0 & s \notin t^\bullet \end{cases} $$

for each $s \in S$.

Since we consider only T-restricted nets of finite synchronization, ${}^-t$ and t^+ are finite multisets and, therefore, are markings of the corresponding net.

A *process* of a system net is a labelled *occurrence net*, where the labelling establishes the correspondence between the occurrence net and the system net. First, we define an occurrence net.

Definition 4 (Occurrence net)

A net $K = (B, E; \lessdot)$ is an *occurrence net*[2], if

1. the transitive closure of $\lessdot$ is acyclic; the transitive closure of $\lessdot$ will be denoted by $<_K$,
2. for each $b \in B$ holds $|{}^\bullet b| \leq 1$ and $|b^\bullet| \leq 1$,
3. for each $b \in B$ the set $\{b' \in B \mid b' <_K b\}$ is finite, and
4. ${}^\circ K$ is finite.

For clarity, we call a place of an occurrence net *condition* and a transition of an occurrence net *event*.

[2] Remember that by Convention 1 we consider only T-restricted nets.

Definition 5 (Process of a system net)

Let $\Sigma = (N, M)$ be a system net with $N = (P, T; F)$, let $K = (B, E; <)$ be an occurrence net, and $r : B \to S$ be a *labelling (of conditions)*. For a finite subset $Q \subseteq B$ we denote by $r(Q)$ the multiset with $r(Q)[s] = |\{b \in Q \mid r(b) = s\}|$ for each $s \in S$.

The pair $\rho = (K, r)$ is a *process* of Σ iff

1. $r(^\circ K) = M$ and
2. for each $e \in E$ there exists a transition $t \in T$ such that $r(^\bullet e) = {}^-t$ and $r(e^\bullet) = t^+$.

3 Components and their semantics

In this section we formally introduce *components*, show how they are composed, and present a compositional semantics, which is based on the processes defined in the previous section.

3.1 Components

A component is a net with some addition: As shown in the example, we distinguish some places as *input* and *output* places of the component. Moreover, we distinguish two kinds of transitions: *progress* transitions and *quiescent* transitions. A progress transition [Rei95, KW95] of a component which is enabled forever must eventually occur. Most transitions of systems and components are assumed to be progress transitions. Therefore, we set off the quiescent transitions T^q in the formal definition.

Definition 6 (Component)

Let $\Sigma = (N, M)$ be a system net with $N = (P, T; F)$ and let $I, O \subseteq P$ be two disjoint sets with $M[p] = 0$ for each $p \in I \cup O$, and $^\bullet T \cap O = \emptyset$ and $T^\bullet \cap I = \emptyset$. Moreover, let $T^q \subseteq T$. We call $\Gamma = (\Sigma, T^q, I, O)$ a *component*. The component is *closed*, if $I = O = \emptyset$. A closed component is denoted by $\Gamma = (\Sigma, T^q)$, for short.

The elements of I are called *input places*, the elements of O are called *output places*. We have already seen the graphical representation of input and output places by an arrowhead into the corresponding direction. Note, that there is no conflict with the representation of the initial marking, because input and output places are initially unmarked. We call an element of $P \setminus (I \cup O)$ *internal* place and an element of $S \setminus P$ *external place* of Γ. A quiescent transition is represented by a dashed square — in contrast to progress transitions, which are represented as conventional squares.
As indicated in the example, two components can be composed when their internal places are disjoint and their common interface places have opposite directions. Then, the composed system is the union of both components, where common interface places become internal places of the composed system.

Definition 7 (Composition)

For $i \in \{1,2\}$ let $\Gamma_i = (\Sigma_i, T_i^q, I_i, O_i)$ be two components with $\Sigma_i = (N_i, M_i)$ and $N_i = (P_i, T_i; F_i)$.

The components Γ_1 and Γ_2 *have the same interface*, if $P_1 = P_2$, $I_1 = I_2$, and $O_1 = O_2$. The components Γ_1 and Γ_2 are *composable*, if $P_1 \cap P_2 = (I_1 \cap O_2) \cup (I_2 \cap O_1)$ and $T_1 \cap T_2 = \emptyset$.

For two composable components Γ_1 and Γ_2 the composed system $\Gamma = \Gamma_1 \Box \Gamma_2$ is defined by $\Gamma = (\Sigma, T^q, I, O)$ with $\Sigma = (N, M)$ and $N = (P_1 \cup P_2, T_1 \cup T_2; F_1 \cup F_2)$, and $M = M_1 + M_2$, $T^q = T_1^q \cup T_2^q$ and $I = (I_1 \setminus O_2) \cup (I_2 \setminus O_1)$ and $O = (O_1 \setminus I_2) \cup (O_2 \setminus I_1)$

Note, that names of transitions are irrelevant in the semantics of a component, which will be defined later on. Therefore, we assume without loss of generality $T_1 \cap T_2 =$ for two components.
It can be easily checked, that the composition $\Gamma_1 \Box \Gamma_2$ of two composable components is a component again. Moreover, $\Box$ is commutative and associative.

3.2 Semantics

Before defining the compositional semantics for components, we define a *reference semantics* for closed components. This is the semantics in which we are actually interested. The compositional semantics, which we will present later on, is just a tool to reason about this reference semantics in a compositional way.
Essentially, the semantics of a closed component $\Gamma = (\Sigma, T^q)$ is the set of processes of Σ as defined in Sect. 2. The only additional requirement concerns the progress transitions of Γ: A progress condition must occur when possible (i.e. at the "end" K° of a run $\rho = (K, r)$ only quiescent transition are enabled). We call a process of Σ satisfying this additional requirement *closed run* of Γ.

Definition 8 (Reference semantics)

Let $\Gamma = (\Sigma, T^q)$ be a closed component with $\Sigma = (N, M)$ and $N = (P, T; F)$. A process $\rho = (K, r)$ of Σ is a *closed run* of Γ, if for each transition $t \in T$ and each finite set $Q \subseteq K^\circ$ with $r(Q) = {}^-t$ holds $t \in T^q$.

The set of all closed runs of Γ is denoted by $R_{cl}(\Gamma)$.

There are many different temporal logics, which are interpreted on runs. In some way each logic defines when a run ρ *satisfies* a temporal formula φ, which is denoted by $\rho \models \varphi$. We need to know only this relation in order to define the validity of a formula for a closed component: A formula φ is valid for a closed component Γ, if each run $\rho \in R_{cl}(\Gamma)$ satisfies φ. Therefore, the reference semantics is the formal basis for any of these temporal logics. At the end of this paper, we will give a concrete example for such a temporal logic.

Next, we define a compositional semantics for arbitrary components. As we have seen in the introduction, it is necessary to represent some behaviour of the environment in this semantics in order to achieve compositionality. Therefore, an event of a run of a component either corresponds to a transition of the component itself, or it corresponds to an event of its environment. This is captured by distinguishing two cases (2a. and 2b.) in the following definition.

Definition 9 (Semantics for components)

Let $\Gamma = (K, T^q, I, O)$ be a component with $\Sigma = (N, M)$ and $N = (P, T; F)$, let $K = (B, E; <)$ be an occurrence net, and let $r : B \to S$ be a labelling such that

1. $r({}^\circ K)[s] = M[s]$ for each $s \in P$.
2. For each event $e \in E$ one of the following conditions holds:
   (a) There exists a transition $t \in T$ such that $r({}^\bullet e) = {}^-t$ and $r(e^\bullet) = t^+$.
   (b) $r({}^\bullet e)[s] \leq 1$ and $r(e^\bullet)[s] \leq 1$ for each $s \in S$. Moreover, $r({}^\bullet e)[s] = 1$ implies $s \in O \cup (S \setminus P)$ and $r(e^\bullet)[s] = 1$ implies $s \in I \cup (S \setminus P)$.
3. For each transition $t \in T$ and each finite set $Q \subseteq K^\circ$ with $r(Q) = {}^-t$ holds $t \in T^q$.

Then, $\rho = (K, r)$ is a *run* of Γ. The set of all runs of Γ is denoted by $R(\Gamma)$.

Requirement 1 of Def. 9 corresponds to requirement 1 of Def. 5. The difference is that, here, we do not restrict the initial marking for external places (which is not known, because they are part of the environment). Requirement 2.a of Def. 9 corresponds to requirement 2 of Def. 5. However, the other case 2.b allows events that correspond to transitions of the environment. The last requirement concerning progress transitions is identical to the one of closed runs in Def. 8.
A main feature of this semantics is that composition of systems semantically means conjunction. This feature is crucial for modular reasoning in combination with some temporal logic, which will become more evident in Sect. 4.

Proposition 10 (Composition is conjunction)

Let Γ_1 and Γ_2 be two composable components. Then we have $R(\Gamma_1 \Box \Gamma_2) = R(\Gamma_1) \cap R(\Gamma_2)$.

Proof: Let Γ_1 and Γ_2 be composable components and $\Gamma = \Gamma_1 \Box \Gamma_2$ as in Def. 7 and let $\rho = (K, r)$. We have to show: $\rho \in R(\Gamma)$ iff $\rho \in R(\Gamma_1)$ and $\rho \in R(\Gamma_2)$. This can be done for each of the requirements 1–3 of Def. 9 separately.

1. Since Γ_1 and Γ_2 are composable components, we know $P_1 \cap P_2 \subseteq I_2 \cup O_2$. By definition of a component, we know $M_2[s] = 0$ for $s \in I_2 \cup O_2$. Thus by definition of the initial marking of the composed system, $M[s] = M_1[s]$ for each $s \in P_1$. Symmetrically, we get $M[s] = M_2[s]$ for each $s \in P_2$.